

1 NIDs, and installation and engineering costs. The installations included in the
2 VRUC data relied upon by Verizon covered the years 1997, 1998 and 1999.

3 Based on this description, it was our understanding that the VRUC
4 database contained summaries of installed cable costs from a variety of actual
5 Verizon outside plant capital investment projects. However, after reviewing some
6 of the underlying details produced by Verizon in discovery,²⁰ we became
7 convinced that the VRUC unit costs are not derived from actual outside plant
8 placement projects, but instead contain what appear to be estimated cable
9 installation costs resembling those typically found in a cost estimating tool. Most
10 troubling, however, is that year-to-year changes in installed cable prices,
11 particularly between 1997 and 1998, far exceed any reasonable measure of
12 inflation over that period. Because Verizon's installed cable costs are based on an
13 average of the VRUC costs over all three years, the excessive and unsupported
14 inflation in the 1998 and 1988 VRUC costs produce overstated average installed
15 costs.

16 **Q. CAN YOU PROVIDE AN EXAMPLE OF THE EXCESSIVE ANNUAL**
17 **CHANGE?**

18 A. Yes. The following table presents the underground copper cable prices from the
19 VRUC data for 1997 and 1998.

²⁰ Verizon supplemental response to Request AT&T/WCOM 1-11 (a), file
VA_VRUC9799.mdb.

1 **[BEGIN VERIZON PROPRIETARY]**

2 ***

3 **[END VERIZON PROPRIETARY]**

4 As the table shows, the price per foot for these allegedly “actual”
5 installations of underground cable in 1998 are consistently **[BEGIN VERIZON**
6 **PROPRIETARY] *** [END VERIZON PROPRIETARY]** greater than the
7 1997 installed cost.

8 **Q. HOW DO THE INFLATION PATTERNS REFLECTED IN VRUC**
9 **COMPARE TO THE TELEPHONE PLANT INFLATION INDICES?**

10 A. Not well. The following table presents the change from 1997 to 1998 in price-
11 per-foot across cable sizes from Verizon’s VRUC database, Verizon’s
12 corresponding TPIs, and the C.A. Turner TPIs that we discuss in more detail
13 below.

14 **[BEGIN VERIZON PROPRIETARY]**

15 ***

16 **[END VERIZON PROPRIETARY]**

17 As the table demonstrates, the inflation assumptions in VRUC are far out
18 of line with inflation experienced by the telephone industry over the same time
19 period.

20 **Q. ARE THERE OTHER CLUES IN THE UNDERLYING VRUC DATA**
21 **WHICH HELP CONFIRM THAT THE VRUC UNIT COSTS ARE NOT**
22 **BASED ON ACTUAL INSTALLATIONS?**

23 A. Yes. For each of the three distinct types of outside plant cable contained in the
24 VRUC database – aerial, buried and underground – the incremental increase in the

1 installed cost per foot is the same. While this would not necessarily be a problem
2 if the VRUC data measured only the cable material price, it is a big problem here.
3 The VRUC costs are installed costs, which means they include both material and
4 installation labor. It is reasonable to expect that the ratio of installation labor to
5 cable material would be different among the three types of cable, particularly in
6 light of the fact that the installation cost of buried cable includes the cost of
7 digging a trench. However, Verizon's uniform change in installed costs implicitly
8 assumes that the installation labor to material ratio is the same for aerial, buried
9 and underground cable. If the VRUC data were truly derived from actual
10 installations, the difference in the installation labor to material would be captured.

11 **Q. CAN YOU PROVIDE AN EXAMPLE?**

12 A. Yes. The following table sets forth the difference in the 1997 installed cost per
13 foot between 300-pair and 600-pair cable and the difference between 600-pair and
14 900-pair cable for aerial, buried and underground plant from VRUC.

15 **[BEGIN VERIZON PROPRIETARY]**

16 ***

17 **[END VERIZON PROPRIETARY]**

18 **Q. HOW IS THIS A PROBLEM?**

19 A. Verizon uses a regression analysis of the VRUC data to develop the fixed and
20 variable components of installed cable prices for use in the outside plant
21 characteristics module. The assumption of constant incremental costs across
22 cable types renders Verizon's regression analyses and results suspect. For
23 example, the cost of the trench for buried cable does not increase linearly with the

1 size of the cable being installed because the size of the trench itself does not vary
2 considerably based on cable size. Yet, Verizon's VRUC implicitly assumes it
3 does and thereby most likely overstates the trench costs.

4 **Q. HOW DID YOU REMEDY THE PROBLEMS YOU IDENTIFIED IN**
5 **VRUC?**

6 A. While it would be my preference to eliminate Verizon's use of the VRUC data
7 completely from its cost study, the mechanics of the way Verizon's model works
8 renders that an impractical solution. In my restatement of Verizon's costs, we
9 continue to use the VRUC data, but we only use the cost information from 1997
10 indexed forward to 2001 levels based on the appropriate telephone plant index. In
11 this matter, we avoided the overstatement of costs produced by the excessive and
12 unsupported inflation in the VRUC installed costs beyond 1997. However, there
13 is no way to adjust for the seemingly erroneous nature of Verizon's data showing
14 that changes in cost as cable size increases are identical for different types of
15 cable.

16 **Q. ARE VERIZON'S UNIT COSTS FROM VRUC AND OTHER INTERNAL**
17 **SOURCES CORRECTLY ADJUSTED FOR INFLATION?**

18 A. No. Verizon uses inflation rates that are too high. Verizon's unit costs are based
19 on the cost of equipment at the time it was installed in its network adjusted for
20 inflation to determine the ostensible cost in 2001. In this proceeding, Verizon
21 uses a combination of actual and forecasted telephone plant indices (TPIs) to
22 inflate costs in its historical database to 2001 levels. The TPI's used in its cost
23 study were developed by Verizon near the end of 1999 and purport to be Verizon-

1 specific indices based on the inflation Verizon experienced through 1998. To
2 account for inflation beyond 1998, Verizon used an outdated forecast.

3 AT&T and WorldCom have asked Verizon in discovery to provide
4 documentation supporting these Verizon specific indices. To date, we have
5 received only limited supporting documentation. Nonetheless, both the Verizon
6 historical and forecast inflation indices used by Verizon appear high.

7 Verizon has not provided any explanation of why indices developed based
8 on Verizon's own experience in installing facilities within its embedded network
9 are correct to use in a forward-looking cost study. Although Verizon may hazard
10 its own justification, a more reasonable and less prone to bias source for telephone
11 plant inflation is the C. A. Turner telephone plant indices. These are publicly
12 available and are based on the experience of the industry as a whole, not just
13 Verizon's experience. In addition, the Turner indices are more recent than the
14 vintage 1999 figures used by Verizon and thus do not need to rely extensively on
15 forecasted inflation rates. These indices confirm that the inflation levels claimed
16 by Verizon in its TPIs are above those experienced industry-wide. The table
17 below compares the inflation rate for underground copper cable from 1999 to
18 2000 and 2000 to 2001 from the Verizon and C.A. Turner indices.

19 **[BEGIN VERIZON PROPRIETARY]**

20 ***

21 **[END VERIZON PROPRIETARY]**

22 The table shows the Verizon indices are far above those published by
23 Turner. Similar patterns exist for other plant accounts. In our restatement of

Verizon's cost study, we substituted the more current Turner Telephone Plant Index values for the unsupported, forecast indices used by Verizon. We applied the Turner Telephone Plant Indexes to Verizon's VRUC cable costs and to Verizon's historical conduit investment costs.

Q. YOU PREVIOUSLY MENTIONED THAT VERIZON ALSO HAS A PROBLEM WITH METALLIC CABLE SIZING. COULD YOU DESCRIBE THE PROBLEM?

A. Verizon sizes metallic cable in the Plant Characteristics Module based on the average number of working lines within each wire center. The cost of the cable sized to accommodate the number of working lines is derived from the VRUC regressions. Verizon converts these cable costs to an investment cost per working circuit. The costs are then increased through the application of a distribution utilization factor for distribution cable and a separate feeder utilization factor for feeder cable. By developing the investment cost per cable based on the number of working lines and then adjusting the cost upward by a utilization factor, Verizon's methodology fails to reflect that the average cost per pair of metallic cable declines as cable sizes increase.

Q. CAN YOU PROVIDE A SIMPLIFIED EXAMPLE?

A. Yes. Assume there are 300 working lines within a Verizon wire center. Further assume that a 300-pair cable costs \$12.00 per foot, 600-pair cable costs \$20.00 per foot, and the cable utilization factor is 50 percent. Based on the assumption of 300 working lines and a 50-percent utilization factor, a 600-pair cable is needed to serve this hypothetical demand. Rather than use the cost per pair-foot for a 600 pair cable of \$0.033 (\$20.00/600), Verizon begins by assuming a 300-pair cable is

1 needed to serve the 300 working lines. Verizon thus uses the cost per pair-foot for
2 300- pair cable OF \$0.040 (\$12.00/300). To get to the 600-pair size that will
3 actually be placed in the model, Verizon divides by the 50-percent utilization,
4 thereby maintaining an effective cost per pair foot of \$0.04. Simply put,
5 Verizon's method uses the unit cost for 300-pair cable when the model calculates
6 that 600-pair cable is needed. In this simplified example, cable costs are
7 overstated by more than 21%.²¹

8 **Q. HOW DID YOU CORRECT THIS SIZING ERROR IN YOUR**
9 **RESTATEMENT OF VERIZON'S COSTS?**

10 A. Verizon runs a regression on its installed metallic cable costs for aerial, buried,
11 and underground feeder and distribution cable to isolate that portion of the costs
12 that vary with the size of the cable (i.e., the copper pair and splicing costs) and
13 those that do not vary materially with size (i.e., the cable sheath). The fixed and
14 variable components are input to the Plant Characteristics Module and are used to
15 compute cable investment by wire center. As cable sizes increase, the constant or
16 "fixed" portion of the cable costs are spread over more cable pairs, producing a
17 decrease in the average cost per pair. To correct Verizon's sizing flaw, we
18 multiplied the constant portion of the cable regression output by the feeder fill
19 factor for feeder cable and by the distribution fill factor for distribution cable. In
20 this way, when the costs per pair are divided by the utilization factor in the loop
21 module, the resulting cost is consistent with the intended size of the cable.

²¹ $(\$0.04 / \$0.033) - 1 = 0.212$ or 21.2%.

1 **Q. DOES VERIZON USE THE CORRECT FORWARD-LOOKING COST**
2 **PER FOOT OF INSTALLED CONDUIT?**

3 A. No. Verizon develops its installed cost of conduit based on the average cost per
4 duct foot of its historic duct installations in Virginia between 1996 and 2000. In
5 relying on this historical average, Verizon ignores the clear pattern in the
6 historical conduit costs that installed costs per foot decline as the amount of
7 conduit installed increases. Table 2 displays the Verizon installed cable cost per
8 foot sorted by the total miles of conduit installed in each year.

9 **[BEGIN VERIZON PROPRIETARY]**

10 ***

11 **[END VERIZON PROPRIETARY]**

12 Under the TELRIC assumption of scorched-node, the new entrant
13 hypothesized for this costing exercise would be required to install conduit
14 sufficient to serve total demand. Because of the demonstrated economies of scale
15 associated with installing conduit, a conservative starting point for developing the
16 conduit installation cost is not the average of the historical experience used by
17 Verizon, but rather the cost associated with the largest number of miles installed
18 in an individual year, which is far less than the number of miles that would be
19 installed in a reconstructed network. We have used Verizon's installed cost per
20 conduit foot of **[BEGIN VERIZON PROPRIETARY] *** [END VERIZON**
21 **PROPRIETARY]** as the starting point for the forward-looking conduit
22 investment costs.

1 **Q. DOES VERIZON USE THE APPROPRIATE FORWARD-LOOKING**
2 **POLE COST?**

3 A. No. Similar to the way it develops conduit costs, Verizon relies on its historical
4 experience installing poles in Virginia as the source for its forward-looking pole
5 investment. Because Verizon Virginia's pole placements over the past five years
6 are not comparable in scope to the pole installations contemplated under the
7 scorch-node TELRIC assumptions, they do not reflect the economies of scale the
8 forward-looking entrant can achieve in installing poles sufficient to meet total
9 Virginia demand. Similar to the discussion of conduit above, pole installations in
10 the forward-looking network will benefit from the economies of sequential
11 installation, minimizing the amount of mobilization and demobilization
12 attributable to the limited pole installations reflected in Verizon's historical data.
13 A more appropriate forward-looking pole investment is the \$417 per installed pole
14 used by the FCC in its Synthesis Model. We have used this investment cost per
15 pole in my restatement of Verizon's costs.

16 **D. UTILIZATION FACTORS**

17 **Q. DID VERIZON USE THE CORRECT FORWARD-LOOKING**
18 **UTILIZATION FACTORS IN ITS DEVELOPMENT OF CLAIMED UNE**
19 **COSTS?**

20 A. No. As Terry Murray has explained in her separate testimony for AT&T and
21 WorldCom, the fundamental error in Verizon's approach is its assumption that the
22 amount of unused capacity properly charged to current ratepayers is equivalent to
23 the amount of spare capacity that an engineer would include in the design of a
24 plant. This assumption is incorrect: the costing exercise here is conceptually
25 distinct from the task of an outside plant engineer. From a costing perspective,

1 the relevant question is not how much spare capacity should be *built* today, but
2 how much should be *charged* to today's ratepayers in current rates. As Ms.
3 Murray explains, the conceptual answer to the latter (*i.e.*, economic) question
4 requires one to estimate the present value of the future costs of building and
5 operating the capacity over its expected life, and to calculate unit costs based on
6 the net over the same expected life. The resulting cost-based prices will not
7 require current ratepayers to subsidize the future customers on whose behalf the
8 spare capacity is being built. Because an efficient firm would not build spare
9 capacity for future growth unless the present value of the future revenue from the
10 growth capacity exceeded the present value of its cost, the conservative
11 simplifying assumption is to assume away both the existence of future growth in
12 demand *and* the existence of the capacity to meet that growth. Hence, the cost of
13 plant capacity is properly attributed to current ratepayers (including CLECs, with
14 respect to local loops) *without considering any capacity needed for future growth*.

15 Moreover, even if the engineering analysis used to size plant were the
16 correct approach for attributing costs between current and future ratepayers – and
17 it is not – the engineering fill factor or capacity utilization assumptions employed
18 by Verizon in its UNE cost models are derived directly from the utilization of the
19 embedded network. TELRIC hypothesizes an efficient provider of telephone
20 services. Because the new provider is not encumbered by Verizon's embedded
21 plant configuration, it can develop an efficient design that will be able to achieve
22 higher utilization levels than Verizon's embedded plant. In addition, Verizon's
23 analysis of utilization is calculated by dividing only the *working* units or pairs by

1 the total available units or pairs. This assumption is incorrect under standard
2 engineering practice and is even inconsistent with the manner in which Verizon's
3 own engineers define utilization in actual practice. For these reasons, we would
4 recommend the following utilization rates if the Commission were (improperly, in
5 our opinion) to rely on engineering rather than economic analysis to determine the
6 efficient forward-looking amount of spare capacity: a copper feeder utilization
7 rate of 80%; a copper distribution fill factor of 60%; a plug-in equipment
8 utilization of 90%; a fiber feeder utilization of 100%; and a conduit utilization of
9 100%.

10 **1. UTILIZATION OF DISTRIBUTION**

11 **Q. WHAT UTILIZATION FACTOR DID VERIZON USE FOR**
12 **DISTRIBUTION CABLE?**

13 A. Verizon used a [BEGIN VERIZON PROPRIETARY] *** [END VERIZON
14 PROPRIETARY] distribution cable fill factor that was based directly upon the
15 distribution fill levels currently experienced in the embedded network.²² This
16 distribution fill is equivalent to well below the two lines per living unit
17 recommended by the SCC in the prior UNE proceeding and results in unnecessary
18 excess spare capacity in the forward-looking distribution network. Indeed, as
19 applied in the cost study, Verizon's [BEGIN VERIZON PROPRIETARY] ***
20 [END VERIZON PROPRIETARY] spare distribution pairs for each working

²² Verizon Cost Panel Testimony at 112.

1 distribution pair.²³ In other words, Verizon's distribution fill assumption places
2 approximately [BEGIN VERIZON PROPRIETARY] *** [END VERIZON
3 PROPRIETARY] distribution pairs for each household with a single residential
4 telephone line, [BEGIN VERIZON PROPRIETARY] *** [END VERIZON
5 PROPRIETARY] distribution pairs for each household with two telephone lines
6 and [BEGIN VERIZON PROPRIETARY] *** [END VERIZON
7 PROPRIETARY] distribution pairs for households with three telephone lines.
8 Verizon's approach thus requires CLECs to pay for layer upon layer of spare
9 capacity.

10 **Q. BASED ON A FORWARD-LOOKING METHOD FOR DESIGNING**
11 **OUTSIDE PLANT, WHAT IS THE APPROPRIATE DISTRIBUTION**
12 **UTILIZATION FACTOR?**

13 A. A highly conservative copper distribution fill for use in a forward-looking study is
14 60% or even higher.

15 **Q. WHY SHOULD A 60% COPPER DISTRIBUTION FILL BE**
16 **CONSIDERED CONSERVATIVE?**

17 A. In determining the economically appropriate amount of capacity to be attributed to
18 the user of a cable pair, one must consistently treat the costs and potential
19 revenues of spare capacity reserved for future growth. The fill factor resulting
20 from a pure economic analysis, without taking growth into consideration, should
21 be the range of 90% or so. As we discuss below, we have taken a modest amount

²³ [BEGIN VERIZON PROPRIETARY] *** [END VERIZON PROPRIETARY]

1 of growth into account. Even with those growth assumptions, a fill of 60% is still
2 highly conservative.

3 **Q. WHAT ROLE DO ENGINEERING GUIDELINES FOR GROWTH**
4 **CAPACITY PLAY IN DETERMINING APPROPRIATE FILL FACTORS?**

5 A. None directly. As Ms. Murray explains, the question facing the Commission here
6 is different from the one posed by engineering guidelines. Engineers ask how
7 much spare capacity should be built. The Commission's task here is to decide a
8 different question: how much spare capacity should be built *and charged to*
9 *current ratepayers*. As Terry Murray has explained elsewhere, proper
10 consideration of the present value of both the cost and the future revenue –
11 generating demand associated with growth capacity can only decrease, not
12 increase, the unit costs properly attributed to current rate payers. In any event, as
13 we discuss in what follows, application of engineering standards here would also
14 demonstrate that Verizon's proposed utilization rates are substantially too low.

15 **Q. ASSUME FOR THE SAKE OF ARGUMENT THAT THE COMMISSION**
16 **WERE TO USE ENGINEERING STANDARDS, RATHER THAN**
17 **ECONOMIC ANALYSIS, TO DETERMINE THE APPROPRIATE**
18 **AMOUNT OF SPARE CAPACITY. HOW WOULD YOUR PROPOSED**
19 **FILL FACTOR OF 60% FARE AGAINST SUCH A STANDARD?**

20 A. The 60% standard would readily pass muster even if the Commission used as its
21 benchmark the generally accepted engineering standards as the basis for its
22 decision. A forward-looking engineering analysis is not constrained by the
23 engineering rule of thumb that provides for two lines per living unit across the
24 entire service area footprint. Unlike the situation in residential developments in
25 the design phase or under construction, much of the demand in Virginia has been

1 stable for a long time. Thus, a new entrant could construct its network with far
2 fewer than two lines per household and still have significant excess capacity for
3 customers who order second lines. Under scorched-node, for those areas where
4 demand for additional lines has remained stable and is likely to remain so going
5 forward, fewer spare facilities can be provisioned, resulting in more efficient use
6 and higher utilization levels. By tailoring distribution design to meet only the
7 anticipated needs of today's demand, as TELRIC requires, distribution utilization
8 can be improved to levels well above those experienced by Verizon in its
9 embedded network.

10 Moreover, Verizon includes defective pairs as unused pairs in determining
11 its utilization factor. As explained below, there are a significant number of
12 defective pairs in Verizon's network. But in a reconstructed plant with all new
13 plant there would be very few defective pairs. In Mr. Riolo's experience, when
14 new plant is installed, there should be fewer than 1% defective pairs. Thus, these
15 pairs must be removed from the denominator of Verizon's calculation.

16

17 **Q. ASSUME FOR THE SAKE OF ARGUMENT THAT THE COMMISSION**
18 **WERE TO USE THE TRADITIONAL ENGINEERING STANDARD OF**
19 **TWO DISTRIBUTION PAIRS PER HOUSEHOLD, RATHER THAN**
20 **ECONOMIC ANALYSIS OR FORWARD-LOOKING ENGINEERING**
21 **STANDARDS, TO DETERMINE THE APPROPRIATE AMOUNT OF**
22 **SPARE CAPACITY. HOW WOULD YOUR PROPOSED FILL FACTOR**
23 **OF 60% FARE AGAINST SUCH A STANDARD?**

24 **A. The 60% standard would readily pass muster even if the Commission used**
25 Verizon's proposed engineering standards as the basis for its decision. The
26 generally accepted engineering standard for building distribution plant of two

1 lines per household. According to Verizon, residential subscribers in Virginia
2 subscribe on average to 1.18 lines per subscriber location. An 18-percent second
3 line penetration produces a distribution fill of 59 percent.²⁴

4 But the 59% rate is based on Verizon's entirely improper definition of
5 utilization. Verizon defines the utilization factor for copper distribution cable as
6 "the actual utilization of terminated distribution pairs experienced in the Verizon-
7 Va. network with an adjustment for breakage."²⁵ For this rate case, however,
8 Verizon's definition of utilization for copper distribution omits idle dedicated
9 pairs, defective pairs, and connect-through pairs. This definition is at odds with
10 generally accepted industry guidelines, [BEGIN VERIZON PROPRIETARY]
11 *** [END VERIZON PROPRIETARY]

12 In accordance with the Serving Area Concept (SAC), distribution pairs are
13 permanently committed from the interface to each ultimate living unit. The first
14 pair is designated as the primary pair, the second pair is designated as the
15 permanent secondary pair, while all other pairs are designated as re-assignable
16 secondary pairs. Each primary and permanent secondary pair is dedicated and
17 permanently entered into the assignment record. However, engineers include idle-
18 assigned pairs and defective pairs in the numerator of the generally accepted

²⁴ Two lines per living unit produces a distribution fill of 50%. 50% multiplied 1.18 subscriber lines per location increases distribution fill to 59% ($0.50 \times 1.18 = 0.59$).

²⁵ Verizon Cost Panel Testimony at 113.

1 engineering definition of fill factors.²⁶ Similarly, Verizon's own engineering
2 guidelines state that **[BEGIN VERIZON PROPRIETARY] *** [END**
3 **VERIZON PROPRIETARY]**

4 Therefore, when utilization rates are compared with traditionally accepted
5 engineering standards, consistency dictates that the primary and secondary
6 permanent cable pairs should be counted in the numerator of the ratio.

7 Accordingly, two pairs per household -- as opposed to 1.18 lines per subscriber --
8 should be included in the numerator of the fill ratio. Defective pairs should also
9 be included. This is so for a second reason as well. As set forth below in the
10 discussion of fiber feeder, a reconstructed network would have no defective pairs.
11 If these are included, the utilization rate is substantially above the 60% we have
12 conservatively assumed.

13 **Q. VERIZON STATES THAT THE EFFECT OF CHURN WILL REDUCE**
14 **THE COPPER DISTRIBUTION UTILIZATION RATE. DO YOU**
15 **AGREE?**

16 **A.** No. Subscriber churn, as defined by Verizon, would only change the cable pair
17 status from working to idle assigned, with the net result that the utilization fill
18 remains the same. For these reasons, coupled with the fact that any defective
19 cable pairs would also increase the utilization factor, Verizon's Copper
20 Distribution Cable Utilization can conservatively operate with a 60% fill.

²⁶ Two lines per living unit produces a distribution fill of 50%. 50% multiplied 1.18 subscriber lines per location increases distribution fill to 59% ($0.50 \times 1.18 = 0.59$).

1 **Q. VERIZON CLAIMS THAT ITS LOW DISTRIBUTION FILL LEVELS**
2 **ARE NECESSARY TO AVOID COSTLY AND DISRUPTIVE**
3 **REINFORCEMENT OF ITS OUTSIDE DISTRIBUTION PLANT. DO**
4 **YOU AGREE?**

5 A. No. The Verizon Panel defends its low distribution fill factor in part by
6 suggesting that a higher fill will require costly and disruptive relief of the outside
7 distribution plant. That argument is simply a variant of the erroneous claim that
8 current ratepayers should pay for capacity stockpiled to meet future growth.
9 Furthermore, AT&T/WorldCom have asked Verizon Virginia to provide
10 information relating to its distribution relief jobs in its Virginia service territory
11 over the last three years. Although Verizon objected to this request,²⁷ I believe
12 that most of the distribution relief jobs undertaken by Verizon in Virginia were
13 not because of exhausted outside plant facilities, but instead were for replacement
14 of facilities that had deteriorated over time and thus were generating a high
15 number of service trouble reports. This would suggest that Verizon's existing
16 distribution fill levels are so low that it is virtually guaranteed that distribution
17 cable will not exhaust before reaching the end of its useful life. While this may be
18 Verizon's goal in designing its outside plant, it does not reflect the practice of a
19 least-cost, efficient provider.

²⁷ Response to AT&T/WorldCom #1-47.

2. UTILIZATION OF FEEDER

Q. DID VERIZON USE THE CORRECT FORWARD-LOOKING COPPER AND FIBER FEEDER FILL FACTORS?

A. No. For copper feeder, Verizon uses a [BEGIN VERIZON PROPRIETARY] *** [END VERIZON PROPRIETARY] fill factor. For fiber feeder, Verizon uses a [BEGIN VERIZON PROPRIETARY] *** [END VERIZON PROPRIETARY] fill factor.²⁸ Both of these factors are far too low for a forward-looking cost study. For fiber cable, Verizon's fiber provisioning practices as described in its engineering guidelines support a fill factor for fiber feeder of 100 percent. Because copper feeder cable is engineered to be reinforced on a 3-to-5 year basis, the appropriate forward-looking fill factor for copper feeder is 80 percent.

a) Fiber Feeder Utilization

Q. VERIZON CLAIMS THAT THE APPROPRIATE FORWARD-LOOKING FIBER FEEDER UTILIZATION IS 41.8%. DO YOU AGREE?

A. No. Verizon states that 41.8% represents its current utilization of fiber feeder, and asserts that "[t]here is no basis to believe this utilization rate would increase in the forward-looking network."²⁹ Verizon claims that this low utilization rate is caused by the 12-fiber ribbon structure which necessitates provisioning of excess

²⁸ See Verizon Cost Panel Direct at 100.

²⁹ See Verizon Cost Panel Direct at 112.